

## Intelligent Optribution Outdoor Chassis



*The final product may vary from the above image depending on the options selected.*

### Product:

**DEV 7152**

Intelligent Optribution Outdoor Chassis; 5 Slots

### Features:

- ▀ Rigid Outdoor Chassis for up to 5 Optical Modules
- ▀ 50 Ohm, SMA (f) or N (f), or 75 Ohm, F (f)
- ▀ 1+1 Redundancy Options
- ▀ Automatic Switch Back Option for 1+1 Redundancies
- ▀ 4+1 Redundancy Options
- ▀ RGC (Redundancy path Gain Compensation) for n+1 Redundancy
- ▀ Optical Ethernet Options
- ▀ SNMP Support
- ▀ DEV Web Interface
- ▀ Signal Recording and Data Backup Feature
- ▀ Power Supply Redundancy
- ▀ Pole Mount Assembly
- ▀ Extended Temperature Range -30...+60 °C (-22...+140 °F)

## DEV 7152 Intelligent Optribution Outdoor Chassis; 5 Slots

	Value	Condition
<b>Capacity</b>		
Front Side	5 Slots for Optical Modules (max. 4 Twin Modules)	
<b>Remote Communication</b>		
Interface (Connector)	Ethernet (RJ-45)	
Remote Control & Surveillance	via Web Interface and via SNMP	
<b>Redundant Power Supply</b>		
Supply Voltage	100...240 V AC	
Power Consumption	<100 VA	
<b>General Specifications</b>		
Size	14.7" (374 mm) Width, 15" (382 mm) Height, 13.2" (335 mm) Depth	
Mounting	via 4 Bolts	
Weight	~17 kg	Empty Chassis
Operating Temperature	-30...+45 °C (-22...+113 °F) -30...+60 °C (-22...+140 °F)	Standard With Option 91

### Option 22 Main Backup Swap

Main Backup Swap enables the dynamic change of main and backup assignment to realize the autonomous switching from the backup link to the main link in addition to the (standard) autonomous switching from the main link to the backup link.

■ Available for 1+1 Rx redundancies

### Option 28 Automatic Switch Back

Automatic Switch Back enables the autonomous switching back from the redundant link to the main link based on the RF Sensing functionality.

■ Available for 1+1 Rx redundancies

### Option 54 SFP Ethernet Module

SFP Ethernet Media Converter card to be applied into one optical slot. Use any SFP module that applies to your installation requirements.

### Option 55 Change Ethernet to optical Ethernet Interface; 30 km

### Option 56 Change Ethernet to optical Ethernet Interface; 1530 nm; 100 km

### Option 57 Change Ethernet to optical Ethernet Interface; 1550 nm; 100 km

### Option 58 Additional Ethernet Port with integrated Switch Functionality; only in Conjunction with Option 55, 56, or 57

With Option 55, Option 56, or Option 57 the CPU module of the device provides a 100Base-FX Ethernet interface with SC/PC connectors (instead of the standard 100Base-TX Ethernet interface with RJ-45 connector) for the optical transmission of Ethernet signals.

With applied Option 58 in addition to one of these options, the device provides a second 100Base-TX Ethernet interface with RJ-45 connector with integrated switch functionality.

### Option 89 Pole Mount Assembly

	Value
Mounting	For Pole Diameters 6.6...10.0" (168...254 mm)

## Cabling Options

Cabling options are used for stand-alone optical Tx or Rx modules.

- ▀ Available in 50 Ohm with SMA (f) or N (f) connectors, or in 75 Ohm with F (f) connectors
- ▀ Available for DC...3000 MHz, or for 10...1006 MHz, or for DC, 700...2500 MHz

## 1+1 Redundancy Options

1+1 redundancy options are used to realize a redundant optical link to a dedicated main link.

- ▀ 1+1 redundancy options are available in 75 Ohm with F (f) connectors or in 50 Ohm with N (f) connectors
- ▀ Up to 2\* with single link modules and up to 4\* with twin modules (see Slot Requirements below)
- ▀ A mix of Tx and Rx redundancies is allowed (see Slot Requirements below)
- ▀ A mix of single link modules and twin modules is not allowed
- ▀ A mix with stand-alone optical Tx or Rx modules is allowed
- ▀ A mix with an n+1 redundancy option is not possible
- ▀ Link gain will be decreased by ~5 dB

	Value	Condition
Return Loss	>14 dB	
Slot Requirements (including Tx/Rx Modules)	<ul style="list-style-type: none"> <li>• 2 Slots for one 1+1 Tx Redundancy with Single Link Modules</li> <li>• 2 Slots for two 1+1 Tx Redundancies with Twin Modules</li> <li>• 4 Slots for two 1+1 Tx Redundancies with Single Link Modules</li> <li>• 5 Slots for four 1+1 Tx Redundancies with Twin Modules</li> <li>• 3 Slots for one 1+1 Rx Redundancy with Single Link Modules</li> <li>• 3 Slots for two 1+1 Rx Redundancies with Twin Modules</li> <li>• 5 Slots for two 1+1 Rx Redundancies with Single Link Modules</li> <li>• 5 Slots for one 1+1 Tx &amp; one Rx Redundancy with Single Link Modules</li> <li>• 5 Slots for two 1+1 Tx &amp; two Rx Redundancies with Twin Modules</li> </ul>	

## N+1 Redundancy Options

N+1 redundancy options are used to provide a redundant optical link to a number of main links.

- ▀ Available for DC, 950...2150 MHz
- ▀ Available in 50 Ohm with SMA (f) or N (f) connectors, or in 75 Ohm with F (f) connectors
- ▀ A single 4+1 redundancy option can be installed
- ▀ A mix with stand-alone optical Tx or Rx modules is allowed
- ▀ A mix with an 1+1 redundancy option is not possible
- ▀ Redundancy path **Gain Compensation**) (RGC) to align the gain of the redundant link with the related main link in case of redundancy switching
- ▀ Link gain will be decreased by ~2 dB for main links

	Value	Condition
Number of Main Channels (n)	4	
Return Loss (Signal Path)	>14 dB	
Slot Requirements (including Tx/Rx Modules)	<ul style="list-style-type: none"> <li>• 3 Slots with Twin Modules</li> <li>• 3 Slots with 1 Single Link Module (Redundancy Channel) and with 2 Twin Modules (Main Channels)</li> <li>• 5 Slots with Single Link Modules</li> </ul>	

## Order Information

### Optribution Chassis

DEV 7152	Intelligent Optribution Outdoor Chassis; 5 Slots
Option 22	Main Backup Swap
Option 28	Automatic Switch Back
Option 55	Change Ethernet to optical Ethernet Interface; 30 km
Option 56	Change Ethernet to optical Ethernet Interface; 1530 nm; 100 km
Option 57	Change Ethernet to optical Ethernet Interface; 1550 nm; 100 km
Option 58	Additional Ethernet Port with integrated Switch Functionality; only in Conjunction with Option 55, 56, or 57
Option 89	Pole Mount Assembly
Option 91	-30...+60 extended Temperature Range

### Cabling Options

Option 40	Cabling for 1 Slot; DC...3000 MHz; 50 Ohm, SMA (f)
Option 40 Twin	Cabling for 1 Slot for Twin Module; DC...3000 MHz; 50 Ohm, SMA (f)
Option 40/N	Cabling for 1 Slot; DC...3000 MHz; 50 Ohm, N (f)
Option 40/N Twin	Cabling for 1 Slot for Twin Module; DC...3000 MHz; 50 Ohm, N (f)
Option 41	Cabling for 1 Slot; 10...1006 MHz; 75 Ohm, F (f)
Option 42	Cabling for 1 Slot; DC, 700...2500 MHz; 75 Ohm, F (f)
Option 42 Twin	Cabling for 1 Slot for Twin Module; DC, 700...2500 MHz; 75 Ohm, F (f)

### 1+1 Redundancy Options

Option 45/50N/Rx	1+1 Rx Redundancy Kit; 950...2150 MHz; 50 Ohm, N (f)
Option 45/50N/Tx	1+1 Tx Redundancy Kit; DC, 950...2150 MHz; 50 Ohm, N (f)
Option 45/75/Rx	1+1 Rx Redundancy Kit; 950...2150 MHz; 75 Ohm, F (f)
Option 45/75/Tx	1+1 Tx Redundancy Kit; DC, 950...2150 MHz; 75 Ohm, F (f)

### N+1 Redundancy Options

Option 47/50/4+1	4+1 Redundancy Kit; DC, 950...2150 MHz; 50 Ohm, SMA (f)
Option 47/50N/4+1	4+1 Redundancy Kit; DC, 950...2150 MHz; 50 Ohm, N (f)
Option 47/75/4+1	4+1 Redundancy Kit; DC, 950...2150 MHz; 75 Ohm, F (f)

## Contact

DEV Systemtechnik GmbH  
Grüner Weg 4A  
61169 Friedberg  
GERMANY  
Phone: +49 6031 6975 100  
Fax: +49 6031 6975 114  
info@dev-systemtechnik.com  
www.dev-systemtechnik.com

Rev. 17-Mar-2020

*Technical specifications are subject to change*